

Extensa 5230 seriesEX5230-571G16Mi
LX.EBA0Y.071

Operating system	Windows Vista™ Home Basic (Greek)
Platform	Intel® Celeron® mobile processor, featuring: Intel® Celeron® mobile processor 575 (2.00 GHz, 667 MHz FSB, 3 MB L2 cache), supporting Intel® 64 architecture · Mobile Intel® GL40 Express Chipset · Acer InViLink™2 802.11b/g Wi-Fi CERTIFIED® network connection, supporting Acer SignalUp™ wireless technology
Memory	1 GB DDR2 667MHz soDIMM (1*1GB)
Display	15.4" WXGA high-brightness TFT LCD, 1280 x 800 pixel resolution, supporting simultaneous multi-window viewing via Acer GridVista™
Graphics	Mobile Intel® GL40 Express Chipset with integrated 3D graphics, featuring Intel® Graphics Media Accelerator 4500M (Intel® GMA 4500M) with up to 1759 MB of Intel Dynamic Video Memory Technology 5.0 (64 MB of dedicated video memory, up to 1695 MB of shared system memory), supporting Microsoft® DirectX® 10 Dual independent display support 16.7 million colors External resolution/refresh rate: · 2048 x 1536: 75/60 Hz · 1920 x 1440: 85/75/60 Hz · 1920 x 1200: 75/60 Hz · 1920 x 1080: 100/85/75/60 Hz · 1600 x 1200: 120/100/85/75/60 Hz · 1600 x 900: 120/100/85/75/60 Hz · 1400 x 1050: 85/75/60 Hz · 1280 x 1024: 120/100/85/75/60 Hz · 1280 x 960: 85/75/60 Hz · 1280 x 768: 85/75/60 Hz · 1280 x 720: 100/85/75/60 Hz · 1024 x 768: 120/100/85/75/60 Hz · 800 x 600: 120/100/85/72/60 Hz MPEG-2/DVD decoding WMV9 (VC-1) and H.264 (AVC) decoding
Storage	160 GB 5-in-1 card reader, supporting : Secure Digital™ (SD) Card, MultiMediaCard (MMC), Memory Stick® (MS), Memory Stick PRO™ (MS PRO), xD-Picture Card™ (xD) 8X DVD-Super Multi double-layer drive · Read : 24X CD-ROM, 24X CD-R, 24X CD-RW, 8X DVD-ROM, 8X DVD-R, 8X DVD+R, 6X DVD-ROM DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD+R DL (double-layer), 6X DVD-RW, 6X DVD+RW, 5X DVD-RAM · Write : 24X CD-R, 10X CD-RW, 8X DVD-R, 8X DVD+R, 4X DVD-R DL (double-layer), 4X DVD+R DL (double-layer), 6X DVD-RW, 8X DVD+RW, 5X DVD-RAM
Dimensions and weight	360 (W) x 267 (D) x 30.3/43 (H) mm 3.02 kg with 8-cell battery pack 2.88 kg with 6-cell battery pack
Power subsystem	ACPI 3.0 CPU power management standard: supports Standby and Hibernation power-saving modes 71 W 4800 mAh 8-cell Li-ion battery pack: · 5-hour battery life 48.8 W 4400 mAh 6-cell Li-ion battery pack: · 2.5-hour battery life 2.5-hour rapid charge system-off 3.5-hour charge-in-use 3-pin 65 W AC adapter ENERGY STAR® 4.0

Extensa 5230 series**EX5230-571G16Mi
LX.EBA0Y.071**

Input devices	88-/89-key Acer FineTouch™ keyboard with 5-degree curve, inverted "T" cursor layout, 2.5 mm (minimum) key travel 12 function keys, four cursor keys, two Windows® keys, hotkey controls, embedded numeric keypad, international language support, independent US dollar and Euro symbol keys Empowering Key Easy-launch buttons: email, Internet, programmable Productivity keys: Lock, Presentation, Sync, Front-access switches: WLAN, Bluetooth®
Audio	Two built-in Acer 3DSonic stereo speakers High-definition audio support MS-Sound compatible Built-in microphone
Communication	WLAN: Acer InViLink™ 802.11b/g Wi-Fi CERTIFIED® network connection, supporting Acer SignalUp™ wireless technology LAN: Gigabit Ethernet supporting ASF (Alert Standard Format) 2.0, Wake-on-LAN ready Modem: 56K ITU V.92 with PTT approval ⁹ , Wake-on-Ring ready
I/O interface	ExpressCard™/54 slot PC Card slot (Type II) Acer Bio-Protection fingerprint reader 5-in-1 card reader (SD™, MMC, MS, MS PRO, xD) Three USB 2.0 ports External display (VGA) port Headphone/speaker/line-out jack Microphone-in jack Line-in jack Ethernet (RJ-45) port Modem (RJ-11) port DC-in jack for AC adapter
Security	BIOS user, supervisor, HDD passwords, Kensington lock slot
Software	Acer Empowering Technology (Acer eDataSecurity, ePower, eRecovery, eSettings Management) Acer Crystal Eye Acer GridVista™ Acer Launch Manager Adobe® Reader® Corel® WinDVD McAfee® Internet Security Suite Microsoft® Office Ready 2007 (Office Professional 2007) NTI Media Maker™
Warranty	One-year International Travelers Warranty (ITW)

Product Specifications may vary or/and change without advice